

JDK Audio R20 2-Channel Mic-Preamp

999-0843

Technical Specifications



Inputs: Balanced XLR Mic jack (rear)

Un-Balanced 1/4" Instrument jack (front)

Outputs: Balanced XLR and 1/4" parallel jacks

Microphone Input:

Max Gain: +55dB (no pad), +36dB (w/pad)

Min Gain: +9dB (no pad), -10dB (w/pad)

Pot Gain Range: 46dB

Pad: -20dB

Input Impedance: 6.8k Ohms

Bandwidth: +/- 0.5db, 20Hz - 50kHz

THD+N @ 1kHz, +4dBu: 0.013%

Maximum Level: +20dBu

Signal-to-Noise Ratio: -90dB

Instrument Input:

Max Gain: +31dB (no pad), +21dB (w/pad)

Min Gain: +10dB (no pad), 0dB (w/pad)

Pot Gain Range: 21dB

Pad: -10dB

Input Impedance: 500k Ohms

Bandwidth: +/- 0.5dB, 20Hz - 20kHz

THD+N @ 1kHz, +4dBu: 0.002%

Maximum Level: +20dBu

Signal-to-Noise Ratio: -80dB

Current: 65mA, 7.3VoltAmps

Dimensions: 2U EIA 19" Rack

Height: 3.5 Inches

Width: 19 Inches

Depth: 10 Inches

Weight: 12 lbs